

## Datasheet for #sbcw19525 DN

### Recommendations:

Please read the User Manual and have a look at the FAQ at  
<http://www.alpeslasers.ch/?a=142>

**WARNING:** Operating the laser with higher current or voltage than specified in this document may cause damage and will result in loss of warranty, unless Alpes Lasers has permitted to do so!

**WARNING:** Beware of the polarity of the laser. This laser has to be powered with negative bias and positive bias on the specific zones drawn below. To be used with a high compliance CW laser driver capable of reaching the operating current and voltage indicated in this datasheet, or up to 2.5A/20V.



Figure 1: Mechanical and electrical interface for #sbcw19525 DN (please note that AlN submount numbering is P1131)




Figure 2: Output power as a function of the singlemode emission frequencies and temperatures




Figure 3: Applied DC current as a function of singlemode emission frequencies and temperatures

$\lambda$ [nm]	$\nu$ [cm $^{-1}$ ]	P[mW]	Temp[°C]	$U_{LASER}$ [V]	I[A]
10019.5	998.1	1.6	-10	8.78	0.304
10023.5	997.7	16	-10	9.2	0.35
10027.1	997.3	24.6	-10	9.55	0.385
10031	996.9	30.8	-10	9.94	0.419
10024.7	997.5	0.6	-5	8.88	0.318
10028.1	997.2	10.5	-5	9.25	0.356
10032	996.8	18.4	-5	9.63	0.394
10030.2	997	1.3	0	9.01	0.335
10035.1	996.5	13.2	0	9.5	0.384
10039.3	996.1	18.8	0	9.89	0.42
10035.3	996.5	0.5	5	9.13	0.348
10040	996	9.4	5	9.59	0.394
10041.7	995.8	1	10	9.34	0.371
10047.6	995.3	9.7	10	9.88	0.42

Table 1: Singlemode optical output power as function of operating parameters.




Figure 4: voltage and avg power vs current in continuous-wave operation (the solid squares indicate the maximum singlemode emitted power)

Note: at -10C:  $I_{th}=0.29A$  /  $V_{th}=8.7V$  (2-wires measurements). Maximum operation current: 0.42A for all temperatures.

Figure 3: spectra at different temperatures for various DC currents

