

Datasheet for #sbcw21207 DN

Recommendations:

Please read the User Manual and have a look at the FAQ at <http://www.alpeslasers.ch/?a=142>

WARNING: Operating the laser with higher current or voltage than specified in this document may cause damage and will result in loss of warranty, unless Alpes Lasers has permitted to do so!

WARNING: Beware of the polarity of the laser. This laser has to be powered with negative bias and positive bias on the specific zones drawn below. To be used with a high compliance CW laser driver capable of reaching the operating current and voltage indicated in this datasheet, or up to 2.5A/20V.



Figure 1: Mechanical and electrical interface for #sbcw21207 DN (please note that AlN submount numbering is A0RZW)




Figure 2: Output power as a function of the singlemode emission frequencies and temperatures




Figure 3: Applied DC current as a function of singlemode emission frequencies and temperatures

λ [nm]	ν [cm ⁻¹]	P[mW]	Temp[°C]	U_{LASER} [V]	I[A]
10499.9	952.4	0.4	-20	8.86	0.28
10505.1	951.9	7.6	-20	9.16	0.322
10510.6	951.4	14.2	-20	9.46	0.364
10516.6	950.9	19.5	-20	9.75	0.406
10522.9	950.3	23.5	-20	10.03	0.447
10511.8	951.3	0.4	-10	8.97	0.31
10519	950.7	8.1	-10	9.35	0.363
10525.2	950.1	13.2	-10	9.65	0.405
10531.8	949.5	17.1	-10	9.94	0.447
10525	950.1	0.3	0	9.14	0.344
10534.3	949.3	7.6	0	9.58	0.406
10541	948.7	11.2	0	9.87	0.446
10539.5	948.8	0.2	10	9.34	0.382
10543.3	948.5	2.3	10	9.51	0.406
10550.2	947.8	5.9	10	9.8	0.446
10556.5	947.3	0.2	20	9.62	0.43

Table 1: Singlemode optical output power as function of operating parameters.




Figure 4: voltage and avg power vs current in continuous-wave operation (the solid squares indicate the maximum singlemode emitted power)

Note: at -20C: $I_{th}=0.27A$ / $V_{th}=8.8V$ (2-wires measurements). Maximum operation current: 0.450A for all temperatures.

Figure 3: spectra at different temperatures for various DC currents

